

ALO Nano

Telephone Interface



WARRANTY
18
MONTHS

RESUME

PHYSICAL TELEPHONE INTERFACE, 1 LINE, MINI, ANALOG, PASSIVE

Hybrid telephone interface, portable, to be used for external transmissions and radio and television studios. Has an identical circuit of all the other ALO models and a cabinet that fits in the palm of your hand. Does not require the use of power supply, making it easier to use and its mobility. On the telephone line input and also on the audio inputs and outputs has RFI filters avoiding electromagnetic interference. It also has a protection against electric discharges from the telephone line that protect the equipment. Can work on conventional telephone lines or PBX extensions with variations between 20 and 50V with a minimum current of 20mA.

Balanced audio inputs and outputs with XLR connectors, isolated by transformers that guarantee high quality and immunity to noises, providing a clear and clean sound. Has audio control gain on the back panel. The hybrid circuit (transformation from 2 to 4 wires) is totally electronic and active and has an adjustment for echo cancellation that provides an isolation around 50dB @ 1KHz.

On the front panel, the equipment has a ON/OFF key that attends the telephone call, a call indicator led that is on while the equipment is functioning, a return volume control to the listener and also an audio output volume control to the mixing console. Very versatile, ALO NANO is the ideal equipment for your external transmissions through POTS telephone line with high quality and efficiency and also to be used in transmission and recording studios in order to extract or insert quality audio on the telephone line.

Its case has a high standard finishing with brushed stainless steel panel.

US (Harmonized Code):

8517.18.00.50

DIMENSIONS (Reduced case):

- 120 mm x 43 mm x 110 mm;

- 4,7" x 1,7" x 4,3" pol.;

WEIGHT:

- 0,40 Kg without package;

- 0,55 Kg with package.

CUBAGE:

- 0,00168m³

